

## Company Directive

### STANDARD TECHNIQUE: NC2N

#### Relating to: The ICP Operating Manual

##### Policy Summary

This document provides detailed guidance to the ICP for Design Approval of Associated Contestable Works/Assets and Point of Connection Design Approval of Contestable Connection Works/Assets including the auditing process and the on-site inspection regimes.

Author:	Paul B Smith
Implementation Date:	October 2015
Approved by:	
	Policy Manager
Date:	7 October 2015

**NOTE:** The current version of this document is stored in the WPD Corporate Information Database. Any other copy in electronic or printed format may be out of date.

Copyright © 2015 Western Power Distribution

## **IMPLEMENTATION PLAN**

### **Introduction**

This document has been created to provide an ICP with access to relevant detailed information that is applicable to the Framework Network Access and Adoption Agreement and the associated Extension to Contestability Agreements.

### **Main Changes**

This is a new document.

### **Impact of Changes**

This Standard Technique is for the use of Independent Connection Providers and is intended to provide access to specific guidance that is not otherwise accessible to them.

### **Implementation Actions**

This document shall be made available to Independent Connection Providers within the Tech info site.

### **Implementation Timetable**

This policy shall be implemented on the 28<sup>th</sup> September 2015.

Document Revision & Review Table		
Date	Comments	Author
28/09/2015	<ul style="list-style-type: none"> <li>This document is a new document.</li> </ul>	Paul B Smith

## **1.0 INTRODUCTION**

- 1.1 This document provides detailed guidance to the ICP for the Design Approval of Associated Contestable Works/Assets and Point of Connection Design Approval of Contestable Connection Works/Assets including the auditing process and the on-site inspection regimes.
- 1.2 This document provides access to information for Independent Connection Providers who are signatories to the Framework Network Access and Adoption Agreement and the appropriate Extensions to Contestability that have been made available to facilitate the Code of Practice.
- 1.3 The guidance shall be read in conjunction with WPD Policy and Standard Techniques relating to the New Connections procedures contained within the Technical formation site.
- 1.4 The Operating Manual can be found in Appendix A of this Standard Technique.

# **Design Approval and The Inspection and Monitoring Regime**

## **Operating Manual**

This document provides detailed guidance to staff for the inspection of assets that are to be adopted by WPD that have been constructed by an Independent Connection Provider (ICP) including WPD new connections .



## Document Review Table

Date	Section	Comments	Page

## Contents

Document Review Table.....	2
Section 1 - .....	6
The Inspection and Monitoring Regime .....	6
The Golden Rules for Working with ICPs in WPD .....	8
The Inspection and Monitoring Regime .....	8
Levels of Inspection .....	8
Movement to Lower Inspection Levels .....	8
Eligibility to undertake Self Inspection .....	8
Self- Inspection Membership .....	9
Inclusion of Inspection costs at Quotation Stage .....	9
Billing .....	9
CROWN Inspection Generation .....	10
ICP works .....	10
WPD works .....	10
Fixing the Inspection Level .....	10
Inspection Draw Down .....	10
On Site Inspection.....	11
ICP Works.....	11
WPD Works.....	11
Abortive Site Visit for ICP works only .....	11
Recording Site Visits within CROWN .....	12
Pass .....	12
Fail .....	12
Notifying the ICP of Inspection Results .....	12
Defect Categories .....	12
• Category 1.....	12
• Category 2.....	12
• Category 3.....	12
Failure Processes .....	13
Category 1 Failure Process .....	13
Inspection Level 1 and SIL 1 Failure Notice .....	13

Movement from Self Inspection Level 1 to WPD Chargeable Inspections.....	14
Category 2 Failure Process .....	14
Category 3 Failure Process .....	15
ICP Self Inspection Requirements .....	15
ICP Audit Pack.....	15
Warranty.....	15
Inspection Level Monthly Report .....	15
Rejection Following Submission of a Completion Certificate.....	16
Inspecting WPD Connections work .....	16
 Section 2 – CROWN Calculation and Performance Monitoring .....	 17
Inspection Regime Tables.....	18
Mains .....	18
Services .....	19
Substations .....	19
Final Connections .....	19
EHV Mains UG.....	20
EHV Mains O/H.....	21
EHV Substations - Civil.....	21
EHV Substations - Plant .....	22
Associated 11kV Primary Switchgear .....	24
Poor Performance Flow Chart .....	27
 Section 3 – Inspection and Monitoring CROWN User Guide .....	 28
CROWN Process Outline.....	29
CROWN Routing and processes for Inspecting WPD works.....	30
CROWN determination for the Inspections for WPD work.....	30
CROWN Routing and processes for Inspecting CiC works (Dual offer Option 2 route).....	35
Create an Inspection Regime.....	36
Adding the required activities .....	36
Updating CROWN with the ICP details .....	38
Design Approval Requested .....	39
Design Approval.....	40
Informing the ICP of the technician responsible for the inspections.....	47



Inspection Draw Down .....	55
To Access the Inspection Draw Down Tool .....	55
CROWN Recording of Site Inspection Results (WPD & ICP works).....	58
Adding additional Inspections .....	58
 Section 4 – FAQ’s .....	 60
 Section 5 - Documentation .....	 61
WPD Inspection and Monitoring Regime Notice of Inspection.....	62
Defect Notices .....	62
Inspection Report Forms .....	62
Defect Category Guidance.....	63

## Section 1 - The Inspection and Monitoring Regime

### Contents

The Golden Rules for Working with ICPs in WPD .....	8
The Inspection and Monitoring Regime .....	8
Levels of Inspection .....	8
Movement to Lower Inspection Levels .....	8
Eligibility to undertake Self Inspection .....	8
Self- Inspection Membership .....	9
Inclusion of Inspection costs at Quotation Stage .....	9
Billing .....	9
CROWN Inspection Generation .....	10
ICP works .....	10
WPD works .....	10
Fixing the Inspection Level .....	10
Inspection Draw Down .....	10
On Site Inspection.....	11
ICP Works.....	11
WPD Works.....	11
Abortive Site Visit for ICP works only .....	11
Recording Site Visits within CROWN .....	12
Pass .....	12
Fail .....	12
Notifying the ICP of Inspection Results .....	12
Defect Categories .....	12
• Category 1.....	12
• Category 2.....	12
• Category 3.....	12
Failure Processes .....	13
Category 1 Failure Process .....	13
Inspection Level 1 and SIL 1 Failure Notice .....	13
Movement from Self Inspection Level 1 to WPD Chargeable Inspections.....	14

Category 2 Failure Process .....	14
Category 3 Failure Process .....	15
ICP Self Inspection Requirements .....	15
ICP Audit Pack.....	15
Warranty.....	15
Inspection Level Monthly Report .....	15
Rejection Following Submission of a Completion Certificate.....	16
Inspecting WPD Connections work .....	16

## The Golden Rules for Working with ICPs in WPD

The ICP shall be provided with the same level of services that would be afforded to any other WPD customer. The Assets provided by the ICP shall meet the same standards as our own work, as per G81 and WPD standards and Policies.

Where an ICP presents work for Adoption, WPD staff shall ensure that the work is facilitated in a timely manner.

## The Inspection and Monitoring Regime

WPD's Inspection and Monitoring Regime is the method by which WPD will assess the inspected performance of Connections Business (CB) against an agreed set of criteria that will determine the inspection level that will apply to ICP and WPD.

Where an ICP is at Inspection Level 3 and they meet specific eligibility criteria, they can apply for Self Inspection Level (SIL). To ensure that WPD are adopting serviceable assets that are fit for purpose WPD need oversight of the ICP site inspections, this can be achieved by using a small sampling inspection regime that is undertaken by WPD staff in parallel with the ICP Inspection Regime.

To achieve this we've developed a hybrid regime that incorporates a methodology to allow a CB to move up and down the inspection levels depending on quality of work and volume of inspections.

An ICP may not choose to use the Self Inspection regime, by adopting this approach we will have in place a regime that's consistent for all whether we or they undertake inspections.

## Levels of Inspection

There are three levels of inspection where Inspection level 1 gives the highest level of on-site inspections and 3 the lowest.

All ICPs will initially be allocated to inspection level 1 but may move to lower levels of inspection depending on both performance and volume of works undertaken.

The Self Inspection Regime will allow a CB to undertake site inspections of their own this will reduce the number of inspections that WPD undertake.

For the purpose of sampling the assets that are to be adopted under the Self Inspection regime, there will be two levels of Self Inspection within the Inspection Regime. They are Self Inspection Level 1 (SIL 1) and Self Inspection Level 2 (SIL 2).

## Movement to Lower Inspection Levels

An ICP may move to lower levels of inspection depending on the numbers of inspections and successful performance at the current level of inspection. Successful performance is that level of performance that would either not result in movement of the CB to a lower level (if it is at Inspection Level 3 or SIL 2).

## Eligibility to undertake Self Inspection

To become eligible under the Self Inspection Regime, the ICP shall have been working to the FNA & AA for a minimum of 12 Months **and** have attained Inspection Level 3 during that time.

All ICP's who are eligible to undertake Self Inspection and wish to be included shall be moved from Inspection Level 3 to SIL 2. This will be a Connection Policy Activity.

Some ICP's will only wish to undertake work in specific areas. It shall not be mandatory for an ICP to be considered for Self Inspection across all Activities. Where an ICP wish to undertake new Activities they shall follow the process above for each additional Activity. This is to ensure that the work is to an acceptable standard before they are moved to Self-Inspection. The nominated DM shall have discretion over this process.

Where a CB is removed from Self Inspection due to poor performance, they shall not be considered for Self Inspection for a 12 month. During the 12 month they shall attain Inspection Level 3, and shall remain at that level for a full six months in all relevant Activities before being given the opportunity to move back to SIL 2.

### **Self- Inspection Membership**

Provided the ICP meets the requirements of the eligibility process, they can make a request to WPD to become a Self-Inspection ICP.

WPD Connections Policy will send an Extension of Contestability Agreement to the ICP. This document will detail the Categories and Activities that are to be included in the Self-inspection process.

When the ICP returns a signed copy of the EOC they shall be allocated to SIL 2 for each of the Categories and Activities that have been agreed.

Any additional Activities that the ICP wish to introduce at a later date shall meet the eligibility requirement before they are added to the existing Self-inspection regime.

An ICP can elect to leave the Self-inspection regime by providing WPD with 'three months' notice in writing. WPD shall have the same opportunity to withdraw from the Self-inspection process by giving ICP(s) the same notice.

### **Inclusion of Inspection costs at Quotation Stage**

If the ICP is known at the quotation stage, a check shall be made to see if the ICP has Self Inspection Level in the FNA&AA credential spreadsheet. If the ICP has the EOC for SIL, then inspections costs for the activities outlined in their EOC will not be charged for. All other activities outside of the EOC for SIL shall be treated as Level 3 if the ICP is known during the quotation stage and Level 1 if they are unknown.

It is unlikely that the ICP will be in a position to provide a scheme that will allow the Planner to provide an accurate estimate of the number of inspections and visits required. In this circumstance an estimate shall be made based on historical information of the scheme type and included with the enquiry information. The estimated number of inspections may also be calculated by taking the contestable elements of the WPD design (Option 1) and basing the estimated inspections on this information.

### **Billing**

The connection charge payee shall be billed in advance for the estimated number of Inspections and Visits to be carried out; the inspection costs shall be added to the quote as an extra with on costs removed.

If the ICP is known at the quotation stage and they have the EOC for Self Inspection, no inspection charge shall be included in the quotation.

On completion of the scheme the actual number of visits shall be compared with the estimated number of visits that have been paid for.

- Where a refund is due, this shall be calculated and issued to the original connection charge payee.
- Additional inspections carried out due to revisits for failed inspections shall be invoiced to the ICP for payment.

- Where WPD have miss-calculated and not charged sufficiently for inspection costs, this will be identified at the end of the scheme and the connection charge payee shall be invoiced accordingly for any additional visits omitted (other than re-visits for failed inspections).

Connection to the WPD existing network shall continue to be billed retrospectively as detailed in ST: NC2L.

## **CROWN Inspection Generation**

### **ICP works**

On completion (approval) of the Design Approval CROWN activity, the Planner shall itemise the ICP's design and enter the values into CROWN (lengths of cable, number of joints etc.). CROWN will automatically determine the number of inspections and visits required for the scheme that has been provided by the CB.

See [Design Approval](#)

### **WPD works**

#### ***For LV and HV works***

CROWN will calculate the number of inspections from the WPD quote SWE's automatically upon completion of the 'Accept Quote' activity. The activity 'ICP Inspection' shall be automatically added to the activity list. Generated inspections (if applicable) will be displayed in the CROWN Draw Down Tool as 'outstanding'.

See [CROWN determination for the Inspections for WPD work](#)

#### ***For EHV works***

CROWN is unable to calculate the required inspections automatically. The planner will need to add the required inspections manually.

## **Fixing the Inspection Level**

When the CROWN system process is complete the Scheme will be fixed at the CB Inspection level, this information is held within the CROWN system. The inspection level for the scheme is fixed and will not change for the duration of the Scheme.

The connection to WPD existing network will be continuously updated based on volume of inspections.

## **Inspection Draw Down**

The CB shall provide a program of work that they intend to carry out. This shall be a daily whereabouts notification delivered to the local NS team on the Monday 5 working days prior to works commencing (for all Voltage levels). They shall provide updates as the scheme progresses to allow WPD to carry out on-site Inspections.

The CROWN facility provides a draw down tool where the system will calculate the number of inspections required for the scheme based on the amount of work that the CB has indicated that they intend to carry out for that stage of the work.

This is intended as an indication of the number of inspections and visits that are required. In some circumstances all the inspections could have been carried out for that specific Activity and therefore no further inspections are required for that Activity. The system also provides an indication of the number of completed visits and provides a total of outstanding or not required visits for the scheme.

ICP connection to WPD existing network shall be notified automatically via CROWN following the process contained within ST: NC2L.

## On Site Inspection

### ICP Works

When an ICP has provided a program of work, the WPD inspector shall enter the quantities in to the Inspection Draw Down in the CROWN system. The Inspection Draw Down will provide the number of inspections and visits required for the given quantities. The number of outstanding visits will be displayed on the page to assist the Inspector. With an indication of the number of inspections required, the WPD Inspector shall visit site and inspect the work. This inspection shall be recorded on the appropriate Inspection and Monitoring Site Report. Where there is an opportunity to combine a number of inspections during one visit it shall be done.

See [Inspection Draw Down](#).

### WPD Works

If CROWN has generated inspections for WPD works, the planner shall use the Draw Down tool to work out the required inspections and provide the technician with a list of required inspections on a 'Required inspections form'. As the work presents, the technician shall carry out the required inspections and fill out the correct site report forms for the nature of the work.

See [CROWN determination for the Inspections for WPD work](#)

### Abortive Site Visit for ICP works only

The following process shall apply where an ICP has provided a program of work to WPD and the WPD inspector attends site following the information provided within the program to find the work is not ready for inspection.

The inspector shall record the failed visit as follows:

- Complete the appropriate site report and state the reason for not undertaking the inspection.
- Pass to Team Support.
- Team Support to record the failed inspection as 'Outstanding' and save as a visit (see Team Support user guidance notes).
- Team Support to email the report to the ICP with appropriate cover letter (in NEWCON drive).
- Keep a copy of the site report.

When the activity is ready for inspection

- Carry out inspection, reporting using the appropriate inspection form.
- Pass report and evidence (if applicable) to Team Support.
- Team Support to record inspected activity by changing result from 'Outstanding' to either 'Pass' or 'Fail' (dependent on inspection outcome) and saving the visit (see Team Support user guidance notes).

## Recording Site Visits within CROWN

### Pass

Where the work has been completed to an acceptable standard this shall be recorded as a 'Pass' in the CROWN system. The Inspection and Monitoring Site Report shall be emailed to the ICP with the appropriate cover letter and a record stored locally.

### Fail

Where failures occur, the defects identified shall be recorded on the appropriate form. Failed activities are pre-allocated a severity Category 1, 2 or 3. Failures shall be entered into CROWN with the result 'Fail' and the appropriate defect category identified.

The results for all inspections shall be entered into CROWN as soon as possible after the inspection has been completed.

### Notifying the ICP of Inspection Results

The Inspectors report shall be sent to the ICP, with photographs where appropriate within two working days following the issue of an automated email by CROWN.

Inspection reports containing failures shall always be forwarded to the Connections Policy Team in an electronic format to the appropriate address:

- wpdconnections@westernpower.co.uk (South Wales and South West)
- wpdconnectionpolmids@westernpower.co.uk (Midlands)

The Connections Policy Team shall file the Information for Future Reference within Fortis.

The Inspector shall keep a local record.

### Defect Categories

There are three types of Category failures:

- **Category 1:** is a severe or dangerous defect where there is a serious non-compliance with WPD's policies and procedures or the Framework Network Access and Adoption Agreement. Such defect will result in immediate suspension of that specific Activity of work by that CB ICP on that site.
- **Category 2:** is a serious defect where there is a serious non-compliance with WPD's policies and procedures or the Framework Network Access and Adoption Agreement (FNA&AA). Such defect may not be recoverable at the time of inspection, may result in failure to adopt the asset until rectified. Further inspections will normally be required and gives a failure score of 4. In this instance WPD may determine the action required to rectify the defect.
- **Category 3:** is a minor defect resulting from a minor non-compliance with WPD's policies and procedures or the FNA&AA. Such defect will normally be recoverable at the time of inspection, will not require further inspections and gives a failure score of 1.

Defects shall be reported within the CROWN system using the Site Inspection form.



## **Failure Processes**

### **Category 1 Failure Process**

Where a WPD inspector has identified a Category 1 failure this shall be communicated to the Team manager. If the Team Manager agrees with the inspector, the results shall be recorded in the CROWN system registering a Category 1 Failure.

The Inspection and Monitoring Site Report shall be annotated clearly indicating the location(s) and the severity of the defect.

The CROWN system shall be updated as detailed above with the relevant information, any additional chargeable inspection shall be raised within the CROWN system. Copies of the Site Report and any photographs, as appropriate, shall be emailed to the ICP and a copy sent to Connection Policy.

The TM shall contact the ICP to arrange an urgent meeting to discuss the failure(s). The TM will check in the Fortis File to ensure that the ICP has not had any Category 1 Failures or Inspection Level 1 Performance Failure Notices within the last 12 Months.

If any of the above has occurred the TM shall refer the issue to the Responsible DM who has been appointed to manage the poor performance.

The TM will as soon as is reasonably practicable suspend Adoption of the failed activity by the ICP on that site.

The TM shall meet with the ICP and carry out an investigation and agree a program of work to resolve the issues identified. The ICP shall provide in writing, details of how they intend to prevent a reoccurrence.

Provided that the TM is satisfied that the issues have been resolved he shall send the details to the Connections Policy Team for filing.

The TM can then allow the ICP to continue work on site.

CROWN will move the ICP to Inspection Level 1 automatically, following the registration of a Category 1 Failure notice.

### **Inspection Level 1 and SIL 1 Failure Notice**

Where an ICP is at Inspection Level 1 or SIL 1 and due to poor performance, the CROWN system issues an Inspection Level 1 or SIL1 Failure Notice, The Responsible DM Shall:

Contact the ICP to arrange a Meeting to discuss the Poor Performance

Access the historical failure reports held in the Fortis File

Using the historic information where appropriate, discuss the failure(s) and issue(s), as appropriate with the ICP.

Following the meeting, the ICP shall provide in writing to WPD details of how they intend to prevent poor performance in the future.

Where the historic information indicates a Category 1 Failure notice has been issued within the last 12 Months, refer the ICP to Lloyd's for non-compliance.

The DM shall suspend the ICP from undertaking any activity in the four WPD license areas until such time as Lloyd's can report that the ICP has been investigated and they are confident that the ICP has resolved all the issues and are capable of undertaking work to an acceptable standard.

Where Lloyd's have withdrawn the ICPs accreditation WPD will be unable to adopt any further Assets constructed under this accreditation until Lloyd's has reinstated the ICPs accreditation.

If at any time within the next 12 months the ICP has further Category 1 Failure Notices, in any Activity recorded within the CROWN system, or CROWN issues Inspection Level 1 Failure Notice, the DM shall invoke the FNA & AA or NA & AA and refer the ICP to the WPD legal team where the ICP shall be suspended from working in all of the WPD four licensed areas.

All records of meetings and correspondence shall be sent to Connection Policy and filed for future reference. Where a CB is at SIL 1 and the poor performance continues CROWN will call for the CB to be moved back to Inspection Level 3. An email will be sent to the DM who has been appointed to manage the poor performance process.

A meeting will be called to resolve the issues by the DM with the CB. Provided that the DM is happy with the written plan of action, the CB will remain at SIL 1. When sufficient work has been successfully completed CROWN will move the CB back to SIL 2.

A detailed poor performance flow chart is available. See [Poor Performance Flow Chart](#).

### **Movement from Self Inspection Level 1 to WPD Chargeable Inspections**

Where a CB has been moved from self-inspect to Inspection Level 3, due to poor performance, they shall have all of their remaining Activities moved back to Inspection Level 3. They shall not be considered for self-inspect for a minimum of a 12 month following removal from the Self-Inspect regime.

Having been moved back to the higher inspection regime they shall provide satisfactory performance (remain at Inspection Level 3) for a minimum of a 12 month. Provided the work is satisfactory, it shall be at the discretion of the nominated DM to agree if the CB can be moved back to SIL 2.

### **Category 2 Failure Process**

Where a WPD inspector has identified a Category 2 failure, the Inspection and Monitoring Site Report shall be annotated clearly indicating the location(s) and the severity of the defect.

CROWN shall be updated with the relevant details; an additional chargeable inspection shall be raised within the CROWN system. The CROWN system will send an automated email to the ICP. Copies of the Site Report shall be emailed by the Inspector to the ICP and Connection Policy.

The ICP shall notify the Inspector when the remedial works have been completed where a re-inspection shall be carried out.

### **Category 3 Failure Process**

Where a WPD inspector has identified a Category 3 failure, the Inspection and Monitoring Site Report shall be annotated to clearly indicating the location(s) and the severity of the defect.

The CROWN system shall be updated with the relevant details. The system will send a notice to the ICP informing them of the failure.

A copy of the Site Report shall be attached to an email and sent to the ICP and Connection Policy.

## **ICP Self Inspection Requirements**

### **ICP Audit Pack**

Where an ICP is undertaking Self-inspections they shall submit an Audit pack consisting of:

- A record of the site inspections undertaken as appropriate for the inspection level,
- Details of any poor workmanship,
- Commissioning Certificate,
- Test results,
- Schematic drawings,
- Cable records.

Where appropriate to the WPD Inspector, the Inspections shall be stored locally.

### **Warranty**

All work that is adopted by WPD is covered by a 2 year ICP warranty.

However installations within excavations 1.5m or greater in depth are covered for 3 years.

Any assets that are constructed and adopted under the Self-inspection regime shall have a 10 year warranty

When an ICP is working to Self-inspect and any Activity is at Inspection Level 3 or higher, the work will have a 10 year warranty.

Where an ICP moves back to inspection Level 3, all the work shall continue to be subject to a 10 Years warranty.

## **Inspection Level Monthly Report**

All CB who are registered to undertake work in the Connection Policy database shall be sent a web focus report automatically. This report will provide the Inspection Level that the CB has been allocated following the previous months performance.

## Rejection Following Submission of a Completion Certificate

WPD may refuse to connect assets offered by the ICP, examples of which are provided below;

- A program of work has not been provided
- There are omissions or late delivery of the Completion Certificate
- The as-constructed records are inaccurate or incomplete
- The network offered for connection has not been inspected by WPD in accordance with the Inspection Regime;
- The working area or site is deemed unsafe by WPD staff/contractors
- A Principal Contractor, site agent, site security or any other authorized person refuses access to site
- WPD staff are unable to gain sufficient access to a work location with tools or testing equipment
- Any other requirements of appropriate UK legislation affecting the installed assets are deemed by the WPD Inspector not to have been met
- Where appropriate a WPD Rejection Notice shall be emailed to the ICP's nominated contact.

Where WPD is unable to connect and energise because of operational restrictions or force majeure the ICP's nominated contact should be informed in writing as soon as possible and an alternative date agreed for connection to WPD's distribution system.

## Inspecting WPD Connections work

All Connections work shall be inspected and recorded in the same way as the ICP work. The appropriate Managed Unit shall be used to record the connections work within the CROWN system.

## Section 2 – CROWN Calculation and Performance Monitoring

### Contents

Inspection Regime Tables .....	18
Mains .....	18
Services .....	19
Substations .....	19
Final Connections .....	19
EHV Mains UG.....	20
EHV Mains O/H.....	21
EHV Substations - Civil.....	21
EHV Substations - Plant .....	22
Associated 11kV Primary Switchgear .....	24
Approved Designer Audit Table.....	27
Point of Connection Audit Table.....	28
Poor Performance Flow Chart .....	27

## Inspection Regime Tables

Inspection Level 1 to 3							Self-Inspection Level 1 and 2		
Activity	Inspect Level 1	Qualifying count to level 2	Inspect Level 2	Qualifying count to level 3	Inspect Level 3	Calculation	Inspect SIL 1	Qualifying count to SIL 2	Inspect SIL 2
<b>Mains</b>									
LV Mains	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
HV Mains	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
Trenchless	100%	20 Inspections	100%	20 Inspections	100%	1 visit for each 50m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
LV Mains Joints	50%	20 Inspections	10%	20 Inspections	2%	5 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
LV Terminations	50%	20 Inspections	10%	20 Inspections	10%	2 Terminations = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
HV Joints	50%	20 Inspections	20%	20 Inspections	10%	5 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
HV Terminations	50%	20 Inspections	20%	20 Inspections	10%	2 Terminations= 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Pole erection	50%	20 Inspections	20%	20 Inspections	5%	3 Poles = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Spans of conductor installation	50%	20 Inspections	20%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
Final climbing inspection	50%	20 Inspections	20%	20 Inspections	5%	5 Spans = 1 visit (minimum 1 visit)	5%	20 Inspections	2%

<b>Services</b>									
<i>Service cable installation</i>	20%	20 inspections	10%	20 Inspections	2%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
<i>Service Terminations</i>	20%	20 Inspections	5%	20 Inspections	2%	5 Plots = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<i>Service Flight conductor installation</i>	50%	20 Inspections	20%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
<i>Polarity and Loop Impedance Check</i>	50%	20 Inspections	20%	20 Inspections	10%	5 plots = 1 visit (Minimum 1 Site Visit)	5%	20 Inspections	2%
<i>Service Joint</i>	20%	20 Inspections	5%	20 Inspections	2%	5 Plots = 1 visit (minimum 1 site visit)	5%	20 Inspections	2%
<b>Substations</b>									
<i>Foundations/Building</i>	100%	20 Inspections	20%	20 Inspections	5%	1 foundation = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<i>Electrical Plant</i>	100%	20 Inspections	20%	20 Inspections	5%	1 Installation = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<i>HV Substation Pre- Commissioning</i>	100%		100%		100%	1 test = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<i>HV Operations Pre-commissioning</i>	100%	20 Inspections	20%	20 Inspections	5%	1 test = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<b>Final Connections</b>									
<i>LV Connection Activity-connection to pre-existing WPD network</i>	100%	20 Inspections	50%	20 Inspections	10%	5 connections = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<i>HV Jointing Activity – connection to pre-existing WPD network</i>	100%	20 Inspections	50%	20 Inspections	10%	3 connections = 1 visit (minimum 1 visit)	5%	20 Inspections	2%

<b>EHV Mains UG</b>									
33kV Underground cables	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
66kV Underground cables	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
132kV Underground cables	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
All directional drilling (HDD) whether 33kV, 66kV or 132kV.	100%	20 Inspections	100%	20 Inspections	100%	1 installation = 1 visit	5%	20 Inspections	2%
33kV Jointing	50%	20 Inspections	10%	20 Inspections	2%	2 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
33kV Terminations including separable connectors.	50%	20 Inspections	10%	20 Inspections	10%	2 Terminations = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
66kV Jointing	50%	20 Inspections	20%	20 Inspections	10%	2 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
66kV Terminations including separable connectors.	50%	20 Inspections	10%	20 Inspections	10%	2 Terminations = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
132kV Jointing	50%	20 Inspections	10%	20 Inspections	2%	2 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
132kV Terminations including separable connectors.	50%	20 Inspections	10%	20 Inspections	10%	2 Terminations = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Sheath testing of 33kV, 66kV and 132kV cables as per ST: OS10C/2	100%	20 Inspections	20%	20 Inspections	10%	5 tests = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Commissioning testing of 33kV, 66kV and 132kV cables as per ST: OS10C/2.	100%	1				5 tests = 1 visit (minimum 1 visit)			
Pilot Cable [Inspect with power cable]	50%	20 Inspections	10%	20 Inspections	5%	1 visit for each 100m of cable installed (minimum 1 visit)	5%	20 Inspections	2%
Pilot Cable Jointing	50%	20 Inspections	10%	20 Inspections	2%	5 joints = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Pilot Cable Terminations	50%	20 Inspections	10%	20 Inspections	10%	2 Terminations = 1 visit (minimum 1 visit)	5%	20 Inspections	2%



<b>EHV Mains O/H</b>									
<i>Have statutory Clearances been maintained?</i>	100%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Has correct signage been affixed?</i>	100%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Has Correct Anti-Climbing Device's been affixed?</i>	50%	20 Inspections	20%	20 Inspections	5%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Has plant and equipment been installed correctly?</i>	50%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Correct size pole installed and reinstated, in line, in plumb and on twist?</i>	50%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Correct size conductor installed in line with project plans / instructions?</i>	100%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Correct stay types been used, at correct stay angle / spread and on line to bisect the angle?</i>	50%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Has earthing been installed correctly, conductor size and type and readings?</i>	100%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Have approved materials and suppliers been used?</i>	50%	20 Inspections	20%	20 Inspections	10%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<i>Is Phase rotation correct?</i>	100%	20 Inspections	20%	20 Inspections	2%	1 visit per project full compliance required = 1 inspection	5%	20 Inspections	2%
<b>EHV Substations - Civil</b>									
<i>Switch Room / Control Room Substructure</i>	100%	20 Inspections	20%	20 Inspections	5%	1 building= 1 visit (minimum 1 visit)	5%	20 Inspections	2%

Switch Room / Control Room Superstructure	100%	20 Inspections	20%	20 Inspections	5%	1 building = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
LV AC (incl heating / lighting / de-humidification)	100%	20 Inspections	20%	20 Inspections	5%	1 LVAC Installation = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Access Road / Hard-standing / Footway	100%	20 Inspections	20%	20 Inspections	5%	1 feature = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Substation Compound surfacing and pre-formed cable trenches/ troughs	100%	20 Inspections	20%	20 Inspections	5%	1 compound = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Substation Compound Security Fencing and Gates	100%	20 Inspections	20%	20 Inspections	5%	1 compound perimeter = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
Outdoor Terminal Support Structures (inc Foundations)	100%	20 Inspections	20%	20 Inspections	5%	1 bay = 1 visit (minimum 1 visit)	5%	20 Inspections	2%
<b>EHV Substations - Plant</b>									
33kV Switchgear (Indoor) – Installation	50%	10	25%	5	10%	1 switch board = 1 inspection	10%	10	5%
33kV Switchgear (Outdoor) – Installation	50%	20	25%	10	10%	1 circuit breaker / switch = 1 inspection	10%	10	5%
33kV Switchgear – Cold Commission Testing	100%	10	50%	10	10%	1 site = 1 inspection	10%	10	5%
33kV Switchgear – Local Inter-trip Testing	100%	10	50%	5	10%	1 site = 1 inspection	10%	10	5%
33kV Switchgear – Protection Testing	100%	10	50%	10	10%	1 site = 1 inspection	10%	10	5%
33kV Switchgear - Remote inter-tripping (inc test/commission Pilot Cable)	100%	10	100%	5	100%	1 site = 1 inspection	10%	10	5%
33/11kV Transformer - Installation	50%	10	25%	10	10%	1 transformer = 1 inspection	5%	5	2%
33/11kV Transformer – Tap Change & Controls	50%	10	25%	10	10%	1 tap change = 1 inspection	5%	5	2%
33/11kV Transformer – Testing Alarms & Trips	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%
33/11kV Transformer – Pre-energisation Oil Sampling	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%

66kV Switchgear – Installation	100%	20	75%	10	50%	1 circuit breaker or 1 disconnector = 1 inspection [min 2 inspections, 1 of each]	10%	10	5%
66kV Switchgear - Cold Commission Testing	100%	10	75%	5	50%	1 site = 1 inspection	10%	10	5%
66kV Switchgear - Protection Testing	100%	10	75%	10	50%	1 site = 1 inspection	10%	10	5%
66kV Switchgear - Local Inter-trip Testing	100%	10	75%	10	50%	1 site = 1 inspection	10%	10	5%
66kV Switchgear – Remote inter-tripping (inc test/commission Pilot Cable)	100%	20	100%	10	100%	1 site = 1 inspection	10%	10	5%
66/33kV or 66/11kV Transformer - Installation	50%	10	25%	10	10%	1 transformer = 1 inspection	5%	5	2%
66/33kV or 66/11kV Transformer - Tap Change & Controls	50%	10	25%	10	10%	1 transformer = 1 inspection	5%	5	2%
66/33kV or 66/11kV Transformer - Testing Alarms & Trips	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%
66/33kV or 66/11kV Transformer - Pre-energisation Oil Sampling	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%
132kV Switchgear – Installation	100%	20	75%	10	50%	1 circuit breaker or 1 disconnector = 1 inspection [min 2 inspections, 1 of each]	10%	10	5%
132kV Switchgear - Cold Commission Testing	100%	10	75%	5	50%	1 site = 1 inspection	10%	10	5%
132kV Switchgear - Protection Testing	100%	10	75%	10	50%	1 site = 1 inspection	10%	10	5%
132kV Switchgear - Local Inter-trip Testing	100%	10	75%	10	50%	1 site = 1 inspection	10%	10	5%
132kV Switchgear - Remote inter-tripping (inc test/commission Pilot Cable)	100%	20	100%	10	100%	1 site = 1 inspection	10%	10	5%

132/33kV or 132/11kV Transformer - Installation	50%	10	25%	10	10%	1 transformer = 1 inspection	5%	5	2%
132/33kV or 132/11kV Transformer - Tap Change & Controls	50%	10	25%	10	10%	1 transformer = 1 inspection	5%	5	2%
132/33kV or 132/11kV Transformer - Testing Alarms & Trips	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%
132/33kV or 132/11kV Transformer - Pre-energisation Oil Sampling	100%	20	50%	20	10%	1 transformer = 1 inspection	5%	5	2%
110V Battery System	50%	20	25%	20	5%	1 battery system = 1 inspection	5%	5	2%
33kV Fault Thrower	50%	20	25%	10	10%	1 fault thrower = 1 inspection	10%	10	5%
Earthing System – Installation	100%	10	50%	20	10%	1 earth system = 1 inspection	5%	5	2%
Earthing System - Testing	100%	10	50%	20	20%	1 earth system test = 1 inspection	10%	10	5%
<b>Associated 11kV Primary Switchgear</b>									
11kV Primary Switchgear – Installation	50%	10	25%	5	10%	1 switch board = 1 inspection	10%	10	5%
11kV Primary Switchgear – Cold Commission Testing	50%	20	25%	10	10%	1 circuit breaker / switch = 1 inspection	10%	10	5%
11kV Primary Switchgear – Local Inter-trip Testing	100%	10	50%	10	10%	1 site = 1 inspection	10%	10	5%
11kV Primary Switchgear – Protection Testing	100%	10	50%	5	10%	1 site = 1 inspection	10%	10	5%
11kV Primary Switchgear - Remote inter-tripping (inc test/commission Pilot Cable)	100%	10	50%	10	10%	1 site = 1 inspection	10%	10	5%


### Approved Designer Audit Table

<i>Audit Level 1 to 3</i>						<i>Self Audit Level 1 and 2</i>		
<i>Activity</i>	<i>Audit Level 1</i>	<i>Qualifying count to level 2</i>	<i>Audit Level 2</i>	<i>Qualifying count to level 3</i>	<i>Audit Level 3</i>	<i>Self Audit Level 1</i>	<i>Qualifying count to SAL 2</i>	<i>Self Audit Level 2</i>
<i>Metered Demand LV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Demand HV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Generation LV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Generation HV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Demand EHV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Generation EHV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%

**Point of Connection Audit Table**

<i>Audit Level 1 to 3</i>						<i>Self Audit Level 1 and 2</i>		
<i>Activity</i>	<i>Audit Level 1</i>	<i>Qualifying count to level 2</i>	<i>Audit Level 2</i>	<i>Qualifying count to level 3</i>	<i>Audit Level 3</i>	<i>Self Audit Level 1</i>	<i>Qualifying count to SAL 2</i>	<i>Self Audit Level 2</i>
<i>Metered Demand LV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Demand HV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Generation LV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%
<i>Metered Generation HV</i>	100%	<i>Audits 20</i>	50%	<i>Audits 20</i>	25%	5%	<i>Audits 20</i>	2%

## Poor Performance Flow Chart




## Section 3 – Inspection and Monitoring CROWN User Guide

### Contents

CROWN Process Outline – Dual Offer routes .....	29
CROWN Routing and processes for Inspecting WPD works .....	30
CROWN determination for the Inspections for WPD work .....	30
CROWN Routing and processes for Dual offer Option 2 route .....	35
Calculating and including the inspection costs required for the quote .....	35
Create an Inspection Regime.....	36
Adding the required activities .....	36
Updating CROWN with the ICP details .....	38
Design Approval Requested .....	39
Design Approval (where the ICP is not self-approving their design).....	40
CROWN Inspection Calculator .....	43
CROWN Process and enquiry route for CIRT enabled enquiries .....	47
Informing the ICP of the technician responsible for the inspections.....	55
Inspection Draw Down .....	55
To Access the Inspection Draw Down Tool .....	55
CROWN Recording of Site Inspection Results (WPD & ICP works).....	58
Adding additional Inspections .....	58
Defect Category Guidance.....	63



## CROWN Process Outline – Dual Offer routes



## CROWN Routing and processes for Inspecting WPD works

The following steps are required for when a customer accepts and pays for WPD to carry out both the contestable and non-contestable work to provide the connection – Option 1 within the Dual Offer quote.

The following CROWN activities should already be complete:

- ✓ Contact Customer
- ✓ Obtain Information
- ✓ Send Quote
- ✓ Accept Quote – Option 1

Activity	Target Date	Target Changed	Owner Initials	Completed Date	Days Remaining	Trans
Obtain Information	16/09/2015	Yes	SAD	16/09/2015	0	
Contact Customer	17/09/2015		SAD	16/09/2015	1	
Contact Customer-Is Further Help Needed	25/09/2015		SAD	16/09/2015	7	
Contact Customer To Give Update (1)	30/09/2015		SAD	16/09/2015	10	
Contact Customer To Give Update (2)	14/10/2015		SAD	16/09/2015	20	
Contact Customer To Give Update (3)	28/10/2015		SAD	16/09/2015	30	
Send Quotation	04/11/2015		SAD	16/09/2015	35	
Accept Quotation	16/12/2015		SAD	16/09/2015	65	

☐ Diary
 ☒ Trackable

rt\_eqdet

## CROWN determination for the Inspections for WPD work

Upon completing the 'Accept Quote' activity, CROWN will calculate the required inspections automatically for LV and HV works.

The activity 'ICP Inspection' will be added to the activity list automatically by CROWN.

Generate MPAN	29/09/2015				9	
ICP Inspection	30/09/2015				10	
Send Connection Agreement	02/10/2015				12	

To see if inspections are required and have been generated by CROWN, the Draw Down Tool needs to be accessed.

Click 'View'

Open 'Inspection Drawdown'

The screenshot shows a software window titled 'Enquiry Details - Activities'. It contains fields for Name (Jhuytb Vft), Address (L/HAND 6 FLOOR OFFICE, I), and Enquiry (2287090). A 'View' menu is open, showing options like Prompts, Housing Ledger, MPAN Control Sheet, Enquiry History, EBRs, Work Instructions, NOC and Energisation History, ESQCR, Associated Enquiries, Website Questions and Answers, **Inspection Drawdown**, and Raise Project. Below the fields is an 'Activity' section with buttons: Send Quotation, Accept Quotation, Raise Invoice, Payment Received, and Generate MPAN. A date field shows 29/09/2015.

The Inspection Draw Down window will display showing WPD as the ICP and the appropriate license area.

This information is pulled through from the scheme building process.

The screenshot shows the 'Inspection Drawdown' window. It has a yellow confirmation box at the top. Below it are fields for ICP (Western Power Distribution) and Category (Mains). A description field shows 'Western Power Distribution (South Wales) plc'. At the bottom is a table of activities.

Activity	Temp Quantity	Inspection Level	Inspections	Visits	Orig Qu
LV Mains		Sil 2			10
HV Mains		Sil 2			20
Trenchless		Sil 2			0
LV Joints		Sil 2			4

If any inspections have been generated and are required, they will be displayed with a count in the 'Outstanding' column.

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required.

ICP: Western Power Distribution Category: Mains Calculate

Description: Western Power Distribution (South Wales) plc

Activity	Temp Quantity	Inspection Level	Inspections Visits	Original Quantity	Inspections Required	Inspections Outstanding	Inspections Complete	Not Required
LV Mains		Sil 2		100	0	0	0	
HV Mains		Sil 2		200	0	0	0	
Trenchless		Sil 2		0	0	0	0	
LV Joints		Sil 2		4	0	0	0	
LV Terminations		Sil 2		1	0	0	0	
HV Joints		Sil 2		4	0	0	0	
HV Terminations		Sil 2		0	0	0	0	
Pole erection		Sil 2		0	0	0	0	
Spans of conductor install		Sil 2		0	0	0	0	
Final climbing inspection		Sil 2		0	0	0	0	

Total Completed Visits: 0

Cancel

All categories should be checked for generated inspections, navigating between categories using the category selection louver.

### Process to follow if Outstanding Inspections are generated

1. If CROWN indicates inspections are 'Outstanding'
2. Populate the 'Temp Quantity' cell applicable to each activity, which has outstanding inspections, with the amount of work being carried out of that activity type.
3. Click 'Calculate'

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required.

ICP: Western Power Distribution Category: Services Calculate

Description: Western Power Distribution (South Wales) plc

Activity	Temp Quantity	Inspection Level	Inspections Visits	Original Quantity	Inspections Required	Inspections Outstanding	Inspections Complete	Not Required
Service Cable Installation	10	Sil 2		0	0	2	0	
Service Termination		Sil 2		0	0	0	0	
Service Flight conductor in		Sil 2		0	0	0	0	
Polarity and Loop Impedance		Sil 2		0	0	0	0	
Service Joints		Sil 2		0	0	0	0	

Total Completed Visits: 0

Cancel

**Inspection Drawdown**

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required.

ICP: **Western Power Distribution** Category: **Services** **Calculate**

Description: **Western Power Distribution (South Wales) plc**

Activity	Temp Quantity	Inspection Level	Inspections	Visits	Original Quantity	Inspections Required	Inspections Outstanding	Inspections Complete	Not Required
Service Cable Installation		Sil 2			0		0	0	
Service Termination	10	Sil 2	2	1	0		2	0	
Service Flight conductor in		Sil 2			0		0	0	
Polarity and Loop Impedan		Sil 2			0		0	0	
Service Joints		Sil 2			0		0	0	

Total Completed Visits: 0

**Cancel**

The results from the calculation displayed in the 'Inspections' cell(s) shall be transposed onto the 'Required Inspections' proforma template.

The Required Inspections template can be found by clicking on or navigating to the following link:

[F:\Policy LAN page\Policy Dissemination\Links \(do not move or delete\)\IMR2015\Required inspections.xltm](F:\Policy LAN page\Policy Dissemination\Links (do not move or delete)\IMR2015\Required inspections.xltm)

### Process to follow where no outstanding inspections are generated

If upon using the Draw down tool, it indicates no inspections are outstanding across any of the categories, then this means that no inspections are due for any part of the scheme.

The inspections part of CROWN must be closed using the following steps:

Highlight 'ICP Inspection' activity

Click 'Complete'

**Enquiry Details - Activities**

Name: **Jhuytb Vlt**

Address: **L/HAND 6 FLOOR OFFICE, DERWEN HOUSE, COURT ROAD, BRIDGEND, MID GLAMORGAN, CF31 1BN**


Enquiry: **2286839** Category: **Metered Demand HV with LV End Connections** MPAN: **2199996393258**

Activity	Target Date	Target Owner	Completed Date	Days Remaining	Trans
Contact Customer-Is Further Help Needed	28/08/2015	PBS	19/08/2015	7	
Send Quotation	08/10/2015	PBS	19/08/2015	35	
Accept Quotation	19/11/2015	PBS	19/08/2015	65	
Raise Invoice	21/08/2015			2	
Payment Received	28/08/2015			7	
Generate MPAN	02/09/2015			9	
ICP Inspection	03/09/2015			10	
Send Connection Agreement	07/09/2015			12	


**Notes** **Details** **Transfer** **Complete** **Expand** **Diary** **Trackable**

Team: **Income & Connections Team - Admini** **Desktop**

You shall be asked if you want to create an inspection.  
Select 'No'.



This will complete the 'ICP Inspection' activity.



Accept Quotation	16/12/2015		SAD	16/09/2015	65	
ICP Inspection	30/09/2015		SAD	16/09/2015	10	
Raise Invoice	18/09/2015				2	

No further inspection activity will take place and the construction can be carried out without the inspection and monitoring requirement.

### *Construction file handover procedure for WPD works with required inspections*

Upon handover, the technician shall be made aware of all inspections required for the construction stage via the 'Required Inspections' form which has been populated by the planner (see [Process to follow](#)).

The required inspections shall be presented clearly on the template form showing how many inspections are required for each activity type.

See [F:\Policy\\_LAN\\_page\Policy\\_Dissemination\Links\\_\(do\\_not\\_move\\_or\\_delete\)\IMR2015\Required inspections.xltm](F:\Policy_LAN_page\Policy_Dissemination\Links_(do_not_move_or_delete)\IMR2015\Required_inspections.xltm) for form.

The technician shall be made aware of the reporting process and the required blank inspection reporting forms shall be included in the construction file for use when the work presents ready for inspection.

See <\\AVODCS01\NEWCON\CIC\I and MR\Forms for I&MR> for forms.

## CROWN Routing and processes for Dual offer Option 2 route

The following steps are required for when WPD generates a quote for WPD to carry out the non-contestable work only and the customer to appoint an ICP for the contestable elements – Option 2 within the Dual Offer quote.

The following CROWN activities should already be complete:

- ✓ Contact Customer
- ✓ Obtain Information

### Calculating and including the inspection costs required for the quote

As part of the offer WPD must include inspection costs for the contestable works that the ICP could undertake. At the quotation stage, we may not know who the ICP is nor their design.

#### *Procedure to follow if the ICP is known at the quotation stage.*

Firstly a check should be made to see if the ICP has the Extension of Contestability (EOC) for Self Inspection (SIL).

The information is held in the FNA&AA credentials spreadsheet.

See [FNA&AA spreadsheet](#)

Where an ICP has the EOC for SIL, then no inspection costs shall be added to the quote as the ICP will be carrying out self-inspections.

Where the ICP does not have the EOC for SIL, then inspection costs shall be added to the quote.

Determination of the required inspections is done via a Visit Estimation calculator.

See [Inspection calculator](#) (instructions for use are displayed within the calculator itself.)

The required inspections shall be added to the quote as an extra against the category CiC Inspections at the current inspection rate, on-costs removed.

#### *Procedure to follow if the ICP is NOT known at the quotation stage.*

The inspection calculator shall be used to calculate the inspection visits required.

See [Inspection calculator](#)

The planner will take the contestable elements for the design of Option 1, populate the inspection calculator with the scheme details and then use the Inspection Level 1 to determine the inspections required.

Inspections shall be added as an extra to Option 2 under the CiC category; all on-costs shall be removed.

- ✓ Send Quote
- ✓ Accept Quote – Option 2

## Create an Inspection Regime

### Adding the required activities

Open the prepared Enquiry Details Screen.

Activity	Target Date	Target Owner	Completed Date	Days Remaining	Trans
Obtain Information	02/07/2014			0	
Contact Customer	04/07/2014			2	
Send Quotation	30/07/2014			20	
Accept Quotation	30/10/2014			85	
Design Approval Requested	31/10/2014			86	
Raise Invoice	03/11/2014			87	
Payment Received	10/11/2014			92	
Design Approved or Rejected	14/11/2014			96	

Select activity


Add a New Activity.

Activity	Target Date	Target Owner	Completed Date	Days Remaining	Trans
Obtain Information	02/07/2014			0	
Contact Customer	04/07/2014			2	
Send Quotation	30/07/2014			20	
Accept Quotation	30/10/2014			85	
Design Approval Requested	31/10/2014			86	
Raise Invoice	03/11/2014			87	
Payment Received	10/11/2014			92	
Design Approved or Rejected	14/11/2014			96	



Open the Activity List via the LOV

Select 'ICP Inspection'




The screenshot shows a dialog box titled 'Activity Name' with the following fields: 'Activity Name' (text input), 'Tracking Level' (dropdown menu), 'Target Date' (text input), and 'Prompt Period' (text input with a unit of 'days'). There are 'Save' and 'Close' buttons at the bottom. An 'Available Activities List' is open, showing a search bar with 'i%' and a list of activities. The activity 'ICP Inspection' is highlighted in blue. The list includes: 'ICP Drawings Received', 'ICP Drawings to Mapping Centre', 'ICP Inspection', 'ICP Inspection (10)', 'ICP Inspection (11)', 'ICP Inspection (12)', 'ICP Inspection (13)', 'ICP Inspection (14)', 'ICP Inspection (15)', and 'ICP Inspection (16)'. There are 'Find' and 'OK' buttons at the bottom right of the list.

Select Trackable

Enter a target date (6 months ahead).

Click Save and Close



The screenshot shows the 'Activity Name' dialog box with 'ICP Inspection' entered in the 'Activity Name' field. The 'Tracking Level' dropdown is set to 'Trackable'. The 'Target Date' is set to '02/07/2014' and the 'Prompt Period' is set to '2' days. There are 'Save' and 'Cancel' buttons at the bottom.

Using the same method, open the Activity List via the LOV and select 'Enter ICP Information', select Trackable and enter a target date (3 months ahead)

## Updating CROWN with the ICP details

Once you know the chosen ICP's details, the CROWN system must be updated via the following steps.

Select the 'Enter ICP Information' activity

Click Complete

Enquiry Details - Activities

Name: **Dragon Infrastructure**

Address: **avonbank, Feeder Road, Bristol, Bristol, BS2 0TB**

Enquiry: **1990505** Category: **CIC Demand HV**

Activity	Target Date	Target Owner	Completed Date	Days Remaining	Trans
Obtain Information	02/07/2014			0	
ICP Inspection	02/07/2014			0	
<b>Enter ICP Information</b>	<b>02/07/2014</b>			<b>0</b>	
Contact Customer	04/07/2014			2	
Send Quotation	30/07/2014			20	
Accept Quotation	30/10/2014			85	
Design Approval Requested	31/10/2014			86	
Raise Invoice	03/11/2014			87	

Notes Details Transfer Complete Expand

Diary Trackable

Team: **Primary Design - Berndes - Field Crew** Desktop

Click ICP Name LOV and select ICP

ICP Required Information

Please enter the following information regarding this Independent Connection Provider enquiry

ICP Name

MPAN Core

Number of Connections

Work Planned for Week Commencing

LA/PFI/Other

OK

LIST OF LIVE JOINT ICP

Find %

NAME

Harlaxton Engineering Services

Power Jointing & Distribution Services

Sustainable Energy Highways Lighting (SEHL)

Dragon Infrastructure Solutions Ltd

SSE CONTRACTING

Centregreat Ltd

NDS Limited

ICP May Gurney Cartledge


GMP CONTRACTING SERVICES LTD

Find OK Cancel

Enter the number of connections  
(energising connections)

Add a date for work commencing  
(CROWN only allows a Monday)

Select 'Other' from the options.



ICP Required Information

Please enter the following information regarding this Independent Connection Provider enquiry

ICP Name: **Dragon Infrastructure Solutions Ltd**

MPAN Core:

Number of Connections: **1**

Work Planned for Week Commencing: **07/07/2014**

LA/PFI/Other: **Other**

OK Cancel

rt\_jopinfo

## Design Approval Requested

When the ICP design is received,  
CROWN must be updated to confirm  
this.


If the ICP is requesting to Self-approve  
their own design, then must have the  
EOC for self-approval **and** they must  
submit their enquiry via the CIRT  
route.

See [CROWN Process and enquiry  
route for CIRT enabled enquiries](#)

Else...

Highlight 'Design Approval Requested'

Click 'Complete'



Enquiry Details - Activities

Name: **Dragon Infrastructure**

Address: **avonbank, Feeder Road, Bristol, Bristol, BS2 0TB**

Enquiry: **1990505** Category: **CIC Demand HV**

Activity	Target Date	Target Owner	Completed Date	Day Remain
Enter ICP Information	02/07/2014	KEW	02/07/2014	0
Obtain Information	02/07/2014			0
ICP Inspection	02/07/2014			0
Contact Customer	04/07/2014			2
Send Quotation	30/07/2014			20
Accept Quotation	30/10/2014			85
<b>Design Approval Requested</b>	<b>31/10/2014</b>			<b>86</b>
Raise Invoice	03/11/2014			87

Notes Details Transfer Complete Expand

rt\_eqdet

ACTIVITIES ENQUIRY DETAILS SCHEME DETAILS NOTES

Team: **Primary Design - Berndes - Field Crew** Desktop

Enter the date you received the design from the ICP in the 'Date Approval Request Received' cell.

A single click in this cell will populate it with the current date.

Save & Close

Completing 'Design Approval Requested' starts the Guaranteed Standard activity 'Design Approved or Rejected'

**Design Approved or Rejected**

### Design Approval (where the ICP is not self-approving their design)

On receiving the ICP design, WPD shall review it in accordance with ST:SD1F, using the criteria set out in Appendix B. Upon failing to meet the full criteria and / or if design information is missing, then the design shall be rejected with a descriptive comment and the actions required to resolve the issue.

The scheme shall be checked to determine what type of work they are proposing to carry out for the customer. The ICP credentials will need to be checked to make sure they have the appropriate agreements and accreditations in place to carry out such works.

A central spreadsheet showing current agreements is maintained by New Connections Policy which can be located in the NEWCON drive.

<\\AVODCS01\NEWCON\CIC\WPD FNA & AA\2014 NA AA and 2015 FNA AA including extensions V2.xls>

If the ICP does not have the correct agreements for the proposed design, then New Connections Policy shall be contacted for advice – it may be necessary to set up a Triparty agreement for the scheme.

All required adoption agreements must be in place prior to any work being undertaken by the ICP.

When you have decided the outcome of the ICP design, this decision must be reflected in CROWN.

Highlight 'Design Approved or Rejected'

Click 'Complete'

Enquiry Details - Activities

Name: **Dragon Infrastructure**

Address: **avonbank, Feeder Road, Bristol, Bristol, BS2 0TB**

Enquiry: **1990505** Category: **CIC Demand HV**

Activity	Target Date	Target Changed	Owner Initials	Complete Date
Design Approval Requested	31/10/2014		KEW	02/07/2014
Enter ICP Information	02/07/2014		KEW	02/07/2014
Obtain Information	02/07/2014			
ICP Inspection	02/07/2014			
Contact Customer	04/07/2014			
<b>Design Approved or Rejected</b>	<b>16/07/2014</b>			
<b>Send Quotation</b>	<b>30/07/2014</b>			
Accept Quotation	30/10/2014			

Notes Details Transfer Complete Expand

rt\_eqdet

ACTIVITIES ENQUIRY DETAILS SCHEME DETAILS NOTES

Team: Primary Design - Berndes - Field Crew Desktop

Click the magnifying glass

Approve or Reject Designs or view detail. Click on the Close button to Exit the Form.

Target Date	Approval Date	Rejection Date	Approver/Rejecter
16/07/2014			

Close

If you approve the design, enter the date in the Approval Date cell.

If the design does not meet the criteria set out in ST:SD1F Appendix B or more information is required, the design should be rejected. A date shall be inserted into the Rejection Date cell. A reason shall also be provided which will notify CIRT enquiry ICP's the reason why the design is rejected.

A rejection will reactivate 'Design Approval Requested' and stop the GS standard clock.

A follow up call / email is also required to make sure the ICP is aware of what is required.

Design Approval

Enter the Approval or Rejection Date and click on the OK button to Save the record. Please enter Design is to be Rejected. Click on the Cancel button to Exit the Form.

Request Number

Comments

Approval Date

Rejection Date

Reason For Rejection  
(Provide detail of rejection  
for inclusion in E-Mail to ICP)

OK Cancel

[rt\\_design\\_approval](#)

Upon acceptance of the ICP design you will be presented with the Inspection Calculator.

The calculator allows the ICP design to be itemised and entered into CROWN so that the inspections required can be generated.

## CROWN Inspection Calculator

Check the ICP name is correct – if not 'Enter ICP Information' activity will need to be reactivated and completed with the correct information.

Select the appropriate category by clicking the louver

Window

Inspection Calculator

Please confirm the ICP for the scheme and the category for the activities that are to be inspected. Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections. Click on the Save button to save changes or the Close to exit the form without saving any changes.

ICP **Uk Power Solutions Ltd** Category **Mains** **Calculate**

Activity	Quantity	Inspection Level	Inspect (Max)	visits Required	Description
LV Mains	0	Level 3	0	0	1 Visit for each 10
HV Mains	0	Level 3	0	0	1 Visit for each 10
Trenchless	0	Level 3	0	0	1 Visit for each 50
LV Joints	0	Level 3	0	0	5 Joints = 1 Visit (
LV Terminations	0	Level 3	0	0	2 Terminations = 1
HV Joints	0	Level 3	0	0	5 Joints = 1 Visit (
HV Terminations	0	Level 3	0	0	2 Terminations = 1
Pole erection	0	Level 3			
Spans of conductor installation	0	Level 3			
Final climbing inspection	0	Level 3			

Category

Find %

Save

CATEGORY

- EHV Substations - Civil
- EHV Mains UG
- EHV Mains O/H
- Substations
- EHV Substations - Plant
- Mains
- Services
- Point of Connection Audit Table
- Associated 11kV Primary Switchgear

Find

rt\_inspection\_calculator

Enter the ICP work per activity into the 'Quantity' cells.

Once quantities have been entered in the first category click Calculate and Save. This will generate inspections and then save them.

Failure to do this in order will mean inspections are not correctly assigned to the enquiry.

Change category by clicking on LOV. When quantities are completed always click calculate and save before changing category.

Repeat the process for any other categories that are required, click Close.

Window

Inspection Calculator

Please confirm the ICP for the scheme and the category for the activities that are to be inspected. Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections. Click on the Save button to save changes or the Close to exit the form without saving any changes.

ICP **Harlaxton Engineering Servi** Category **Mains**

Activity	Quantity	Inspection Level	Inspect (Max)	visits Required
LV Mains	2000	1	1000	10
HV Mains	1000	1	500	5
Trenchless	0	1	0	0
LV Joints	16	1	8	2
LV Terminations	4	1	2	1
HV Joints	8	1	5	1
HV Terminations	2	1	2	1
Pole erection	0	1	0	0
Spans of conductor installation	0	1	0	0
Final climbing inspection	0	1	0	0


Save

rt\_inspection\_calculator

### How to re-run the Inspection Calculator after it has been closed

If you accidentally close down the Inspection calculator window without fully populating it, follow these steps:

1. Reactivate 'Design Approval Requested'
2. Reactivate 'Design Approve or Rejected'
3. Highlight 'Design Approval Requested'
4. Click 'Complete'



Enquiry Details - Activities

Name: Jhuytb Vft

Address: L/HAND 6 FLOOR OFFICE, DERWEN HOUSE, COURT ROAD, BRIDGEND

Enquiry: 2287091 Category: CIC Demand HV


Activity	Target Date	Target Changed	Owner Initials	Completed Date
Obtain Information	17/09/2015	Yes	SAD	17/09/2015
Contact Customer	18/09/2015		SAD	17/09/2015
Contact Customer-Is Further Help Needed	28/09/2015		SAD	17/09/2015
Contact Customer To Give Update (1)	01/10/2015		SAD	17/09/2015
Send Quotation	15/10/2015		SAD	17/09/2015
Accept Quotation	17/12/2015		SAD	17/09/2015
Enter ICP Information	17/09/2015		SAD	17/09/2015
Design Approval Requested	18/09/2015			

Notes Details Transfer Complete Expand

ACTIVITIES ENQUIRY DETAILS SCHEME DETAILS NOTES

Team: Policy Section - Administration Desktop

5. Write down the existing date
6. Click the delete button
7. Click 'Save'



Design Approval

If requesting Design Approval then enter comment and requested date and click on Save to Save changes.  
If further information is required then click on the Request button and enter date that the further information was requested.

Req No.	Date Received	Target Date	Approval Requestor	Comments
1	17/09/2015	01/10/2015		

Request Additional Info from Customer or Update Existing Request

Request

Req No.	Info Requested Date	Info Received Date	Comments
1			

Save Close



8. Re-enter the date, with the date that you wrote down for point 5

9. Click 'Save' and 'Close'

**Design Approval**

If requesting Design Approval then enter comment and requested date and click on Save to Save  
If further information is required then click on the Request button and enter date that the further info

Date Approval	Reg Request	No	Received	Target Date	Approval Requestor	Comments

Request Additional Info from Customer or Update Existing Request

**Request**

Req No.	Info Requested Date	Info Received Date	Comments
1			

**Save** **Close**

10. Highlight 'Design Approved or Rejected'

11. Click 'Complete'

**Enquiry Details - Activities**

Name: **Jhuytb Vft**

Address: **L/HAND 6 FLOOR OFFICE, DERWEN HOUSE, COURT ROAD, BRIDGEM**

Enquiry: **2287091** Category: **CIC Demand HV**

Activity	Target Date	Target Changed	Owner Initials	Complete Date
Accept Quotation	17/12/2015		SAD	17/09/201
Enter ICP Information	17/09/2015		SAD	17/09/201
Raise Invoice	21/09/2015			
Payment Received	28/09/2015			
<b>Design Approved or Rejected</b>	<b>01/10/2015</b>			
Adoption Agreement Received	26/10/2015			
Adoption Agreement Sent	02/11/2015			
Generate MPAN	09/11/2015			

**Notes** **Details** **Transfer** **Complete** **Expand**

rt\_eqdet

ACTIVITIES **ENQUIRY DETAILS** SCHEME DETAILS NOTES

Team: **Policy Section - Administration** **Desktop**

12. Click Magnifying Glass

et	Approval Date	Rejection Date	Approver/Rejecter
10/2015			

13. Approve the design – click 'OK'

**Design Approval**

Enter the Approval or Rejection Date and click on the OK button to Save the record. Please Design is to be Rejected. Click on the Cancel button to Exit the Form.

Request Number

Comments

Approval Date

Rejection Date

Reason For Rejection  
(Provide detail of rejection for inclusion in E-Mail to ICP)

**OK** **Cancel**

14. The Inspection Calculator will now be displayed, it should still have your data in the fields to which you can add to or delete in the normal way.

**Inspection Calculator**

Please confirm the ICP for the scheme and the category for the activities that are to be. Please enter the quantities of each activity as required, and pressing the calculate button. Click on the Save button to save changes or the Close to exit the form without saving a

ICP **STERLING POWER UTILIT** Category **Mains**

Activity	Quantity	Inspection Level	Inspection (Max)
LV Mains	0	Sil 2	0
HV Mains	200	Level 3	100
Trenchless	0	Level 3	0
LV Joints	3	Level 3	5
LV Terminations	0	Level 3	0
HV Joints	5	Level 3	5
HV Terminations	2	Level 3	2
Pole erection	0	Level 3	0
Spans of conductor installation	0	Level 3	0
Final climbing inspection	0	Level 3	0

**Save**

## CROWN Process and enquiry route for CIRT enabled enquiries

This section shall be read in conjunction with ST:SD1F

Where an ICP wants to self-approve their own designs (both for Parent and POC schemes) they **must use** the online CROWN interface system, CIRT.

If upon providing a customer with a dual offer quote, they accept and pay for option 2 and appoint an ICP who has the EOC for self-approval, the dual offer enquiry must be closed, the ICP must use the CIRT process and raise a new CIRT enquiry.

For help on the CIRT process, see CIRT user guide.

When the ICP raises an enquiry through the CIRT process the category issued will be one of the following:

- CIC Demand LV - ICP Works Only Notification
- CIC Generation LV - ICP Works Only Notification
- CIC Demand HV - ICP Works Only Notification
- CIC Generation HV - ICP Works Only Notification

The CIRT process interfaces with CROWN, and allows the ICP to complete certain activities which in turn informs us of their current position with the enquiry process.

When a CIRT generated enquiry is opened in CROWN the name of the ICP /customer will present with the address of the works.

The enquiry category will be set with the required CIC – ICP works only notification.

By ICP raising this enquiry they are notifying us that they intend on carrying out work to provide a connection to a customer(s).

The screenshot shows the 'Enquiry Details' form in the CROWN system. The form is titled 'Enquiry Details - Enquiry Details' and contains the following fields and buttons:

- Name:** Sterling Power Utilities
- Address:** Monday Site One, Monday Street One Plymouth PL2 3SY
- Enquiry:** 2286888
- Category:** CIC Generation LV - ICP Works Only Notification
- Type Of Communication:** Work Telephone
- Contact Number:** 0121 585 4535
- E-Mail Address:** sblowers@wester
- Reason For Enquiry:** Test SFB 24/08/2015 13:56  
ICP Performing all works, this is for No  
Import Capacity : 10Export Capacity :  
Connection Voltage :LV No. of Conns.
- Start Date:** 24/08/2015
- Completed Date:**
- Send to JMS:** ☐
- PORS Number:**
- Raised By:** Cain, Corina
- Owner:** 1272 - Plymouth City West
- Responsible Person:**
- Buttons:** Docs, P/L Fault, Info, Load, Service, Equipment
- Team:** Policy Section - Administration
- Desktop:**

Blue arrows point from the text on the left to the 'Name' and 'Category' fields.

On receiving the notification (enquiry), the WPD planner shall check to make sure the ICP holds the EOC to carry out the self-determination of the POC and scheme design checking via the FNA&AA spreadsheet.

See [FNA&AA Spreadsheet](#)

The outcome of this check shall be relayed back to the ICP, and the 'Contact customer' activity shall be completed.

The planner shall provide all necessary information to the ICP to allow them to quote as per ST:SD1F.

Enquiry Details - Activities

Name: Sterling Power Utilities

Address: Monday Site One, Monday Street One Plymouth PL2 3SY

Enquiry: 2286888 Category: CIC Generation LV - ICP Works Only Notification

Activity	Target Date	Target Changed	Owner Initials	Completed Date	Days Remaining	Trans
Contact Customer	25/08/2015		SAD	21/09/2015	-18	
POC Issue - ICP Quoted	30/11/2015				50	
POC Acceptance - ICP Quote Accepted	03/03/2016				115	
Contact Customer (2)	10/03/2016				120	
POC Design Submitted - ICP Design	17/03/2016				125	
Adoption Agreement Received	18/04/2016				145	
Adoption Agreement Sent	25/04/2016				150	
Generate MPAN	03/05/2016				155	

Notes Details Transfer Complete Expand Diary

rt\_eqdet

ACTIVITIES ENQUIRY DETAILS SCHEME DETAILS NOTES

Team: Policy Section - Administration Desktop

If the ICP has the correct EOC's in place they can determine the POC and design the scheme under self-approval and issue the customer with a quote for the connection works.

When they have done this the ICP will complete the activity 'POC Issue – ICP Quoted' via CIRT.

Enquiry Details - Activities

Name: Sterling Power Utilities

Address: Monday Site One, Monday Street One Plymouth PL2 3SY

Enquiry: 2286888 Category: CIC Generation LV - ICP Works Only Notification

Activity	Target Date	Target Changed	Owner Initials	Completed Date	Days Remaining	Trans
Contact Customer	25/08/2015		SAD	21/09/2015	-18	
POC Issue - ICP Quoted	30/11/2015		SAD	21/09/2015	50	
POC Acceptance - ICP Quote Accepted	21/12/2015				65	
Contact Customer (2)	30/12/2015				70	
POC Design Submitted - ICP Design	07/01/2016				75	
Adoption Agreement Received	04/02/2016				95	
Adoption Agreement Sent	11/02/2016				100	
Generate MPAN	18/02/2016				105	

Notes Details Transfer Complete Expand Diary

rt\_eqdet

ACTIVITIES ENQUIRY DETAILS SCHEME DETAILS NOTES

Team: Policy Section - Administration Desktop

The ICP shall notify us that the customer has accepted their quote by completion of the 'POC Acceptance – ICP Quote Accepted' activity via CIRT.

Activity	Target Date	Target Owner	Completed Date	Days Remaining	Trans
Contact Customer	25/08/2015	SAD	21/09/2015	-18	
POC Issue - ICP Quoted	30/11/2015	SAD	21/09/2015	50	
POC Acceptance - ICP Quote Accepted	21/12/2015	SAD	21/09/2015	65	
Contact Customer (2)	28/09/2015			5	
POC Design Submitted - ICP Design	05/10/2015			10	
Adoption Agreement Received	02/11/2015			30	
Adoption Agreement Sent	09/11/2015			35	
Generate MPAN	16/11/2015			40	

The ICP shall send the WPD planner the scheme design and design approval compliance form (ST:SD1F Appendix B) to allow us to audit and record the results in CROWN.

When the ICP sends the design and supporting documentation, they shall also complete the 'POC Design Submitted – ICP Design' activity via CIRT.

WPD planner to contact the ICP to confirm receipt of the ICP design.

'Contact customer (2)' activity to be completed.

Where the ICP has self-approved their POC and scheme design (parent) this needs to be recorded. The inspection calculator window will display, allowing the recording of the ICP self-determination and self-approval. During this stage we must also input of the ICP scheme design which will then generate any required inspections to be performed by WPD.

To record that the ICP has determined the POC select 'Point of Connection Audit Table' from the category LOV.

Click 'OK'

Window

Inspection Calculator

Please confirm the ICP for the scheme and the category for the activities that are to be inspected. Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required. Click on the Save button to save changes or the Close to exit the form without saving any changes.

ICP: **STERLING POWER UTILIT** Category: **Mains** **Calculate**

Activity	Quantity	Inspection Level	Inspect (Max)	visits Required	Description
LV Mains	0	Sil 2	0	0	1 Visit for each 100m of cal
HV Mains	0	Level 3	0	0	1 Visit for each 100m of cal
Trenchless	0	Level 3	0	0	1 Visit for each 50m of cabl
LV Joints	0	Level 3	0	0	5 Joints = 1 Visit (minimum
LV Terminations	0				
HV Joints	0				
HV Terminations	0				
Pole erection	0				
Spans of conductor installation	0				
Final climbing inspection	0				

Category

Find %

**CATEGORY**

- EHV Mains UG
- EHV Mains O/H
- Substations
- EHV Substations - Plant
- Mains
- Services
- Point of Connection Audit Table**
- Associated 11kV Primary Switchgear
- Approved Designer Audit Table

**Find** **OK** **Cancel**

Identify what type of scheme the ICP has carried out self-determination of the POC by writing a value of '1' against the appropriate activity name.

Click 'Calculate'

Click 'Save'.

Inspection Calculator

Please confirm the ICP for the scheme and the category for the activities that are to be inspected. Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required. Click on the Save button to save changes or the Close to exit the form without saving any changes.

ICP: **STERLING POWER UTILIT** Category: **Point of Connection Audit** **Calculate**

Activity	Quantity	Inspection Level	Inspect (Max)	visits Required	Description
CIC Demand LV - ICP Works Only	1	Level 1	1	1	TBA
CIC Generation LV - ICP Works Only	0	Level 1	0	0	TBA
CIC Demand HV - ICP Works Only	0	Level 1	0	0	TBA
CIC Generation HV - ICP Works Only	0	Level 1	0	0	TBA

**Save** **Close**

If the ICP has self – approved their own scheme design then using the category LOV select 'Approved Designer Audit Table'.

Click 'OK'.

Category

Find %

**CATEGORY**

- EHV Mains UG
- EHV Mains O/H
- Substations
- EHV Substations - Plant
- Mains
- Services
- Point of Connection Audit Table**
- Associated 11kV Primary Switchgear
- Approved Designer Audit Table

**Find** **OK** **Cancel**

Identify what type of scheme the ICP has carried out self-approval of the parent/site scheme by writing a value of '1' against the appropriate activity name.

Click 'Calculate'

Click 'Save'.

All appropriate categories should now be run through, populating with the ICP scheme details to generate the onsite inspections.

See [CROWN Inspection Calculator](#) for further help.

Next it must be checked to see if the ICP design and/ or POC determination should be audited. To do this, the 'ICP Inspections' activity must be accessed.

Highlight then click 'Details'

If we are required to carry out an audit on the POC or site design, then they shall be shown in the list of activities.

In this example, CROWN is informing us that an audit is required on both the POC design and the site design.

The designs should be audited as per ST:SD1F using the criteria set out in Appendix B.

ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List.

Activity:  Inspection Result:

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
1	Point of Connection		22/02/201			
2	Approved Designer A		22/02/201			

Add Save Close

rt\_jop\_inspections

When the audit is complete, the result shall be recorded in CROWN. The field shall be populated as follows:

Inspector

- Enter your name as the inspector

Completion date

- The date the audit took place

ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List.

Activity:  Inspection Result:

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
1	Point of Connection	Davies, Stephen	22/02/201	21/09/201	Passed	
2	Approved Designer A		22/02/201			

Add Save Close

rt\_jop\_inspections

Result

The overall outcome of the audit.

- Pass, if all appropriate criteria of ST:SD1F Appendix B are met.
- Fail, if any appropriate criteria of ST:SD1F Appendix B are not met.
  - Where a failure occurs, the defect category shall be identified in the defect category cell.

Forms

! Inspection has failed, Please enter a defect category

OK



ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List.

Activity:  Inspection Result:


Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
1	Point of Connection	Davies, Stephen	22/02/201	21/09/201	Passed	
2	Approved Designer A	Davies, Stephen	22/02/201	21/09/201	Failed	Category 2

Add Save Close

rt\_icp\_inspections

Upon entering all of the required information, the entries shall be saved.  
Click 'Save'.

Forms

 Please confirm that you wish to E-Mail an ICP Failure to [mp@pdp.co.uk](mailto:mp@pdp.co.uk)


Yes No

For any failed activities, CROWN will ask if you want to send the failure information to the ICP.  
Click 'Yes'.

You will be asked if you would like to create a re-inspection.

If the ICP is to change their design due to any failures identified, and resubmit it back to you, then 'Yes' should be clicked.

Forms

 Do you wish to create a re-inspection?

Yes No

This will add an extra line in the activity list ready for the result from the additional audit to be recorded.



ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List

Activity  Inspection Result

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
1	Point of Connection /	Davies, Stephen	22/02/201	21/09/201	Passed	
2	Approved Designer A	Davies, Stephen	22/02/201	21/09/201	Failed	Category 2
3	Approved Designer A		21/09/201			

Add Save Close

rt\_icp\_inspections

The audit results shall be saved as a visit in the normal way by entering the visit number, visit date (date of audit) and the Inspector (your name).

Click 'OK'

Enter Visit Details

Please enter the number of Visits required to perform the inspections recorded on the previous form. Click on the OK button to Save the changes or Cancel to Exit the form without Saving.

Visit Number  Visit Date  Inspector

Previous Visits

Visit Number	Visit Date	Inspector

OK Cancel

rt\_icp\_inspections

The audit is now complete and recorded.

## Informing the ICP of the technician responsible for the inspections

Upon populating CROWN with the ICP scheme detail, it is important that the ICP is aware of whom to inform when they know the schedule of work for the construction stage.

The team manager should be consulted with, and it will be their decision as to who is allocated to the site for inspections and any other non-contestable elements for the provision of the connection.

Preferably two technicians should be allocated to a site so that inspections can be covered in the event of a technician being on leave.


The ICP should be made aware of the names and contact numbers and email addresses of the technicians responsible for the site. The manager may want their details included for monitoring.

## Inspection Draw Down

When an ICP provides a work schedule, then the technician will need to check whether any inspections are required for the work being done by the ICP at that time; this is done using the CROWN Draw Down Tool.

### To Access the Inspection Draw Down Tool

Select the Enquiry Details page



The screenshot shows the 'Enquiry Details - Enquiry Details' page in the CROWN system. The page has a menu bar at the top with 'Action', 'Folders', 'Enquiry', 'Activity', 'Scheme', 'View', and 'Help'. Below the menu bar, the title 'Enquiry Details - Enquiry Details' is displayed. The main form contains several fields: 'Name' (Persimon), 'Address' (persimon, Bristol, Bristol, Bristol), 'Enquiry' (2208706), and 'Category' (CIC Demand HV). There are also fields for 'Type Of Communication', 'Contact Number', and 'Reason For Enquiry'. A section for 'Online Updates' includes a checkbox and an 'Address' button. The 'Start Date' is 30/04/2015, and the 'Completed Date' is empty. The 'Send to JMS' checkbox is unchecked, and the 'PORS Number' is empty. The 'Raised By' field is Davies, Stephen, and the 'Responsible Person' is Bagley, Brian. The 'Owner' is 7111 - Swansea West. At the bottom, there are buttons for 'Docs', 'P/L Fault', 'Info', 'Load', 'Service', and 'Equipment'. A link 'rt\_eqdet' is also present. The page has a tabbed interface with 'ACTIVITIES', 'ENQUIRY DETAILS', 'SCHEME DETAILS', and 'NOTES'. The 'Team' is Swansea West - Construction M+R, and the 'Desktop' button is highlighted.

From the menu select 'View'

Click 'Inspection Drawdown'

Action Folders Enquiry Activity Scheme **View** Help

**Enquiry Details - Enquiry Details**

Name **Persimon**

Address **persimon, Bristol, Bristol, Brist**

Enquiry **2208706** Category **EBRS**

Type Of Communication Contact Number

Online Updates ☐

Start Date **30/04/2015** Completed Date

Send to JMS ☐ PORIS Number Raised By **Davies, Stephen**

Owner **7111 - Swansea West** Responsible Person **Bagley, Brian**

**Docs** **P/L Fault** **Info** **Load** **Service** **Equipment**

rt\_eqdet

**ACTIVITIES** **ENQUIRY DETAILS** **SCHEME DETAILS** **NOTES**

Team: **Swansea West - Construction M+R** **Desktop**

Prompts  
Housing Ledger  
MPAN Control Sheet  
Enquiry History  
EBRS  
Work Instructions  
NOC and Energisation History  
ESQCR  
Associated Enquiries  
Website Questions and Answers  
**Inspection Drawdown**  
Raise Project

You will be presented with the following screen, ready for data entry.

**Inspection Drawdown**

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the

ICP **STERLING POWER UTILIT** Category **Mains**

Activity	Temp Quantity	Inspection Level	Inspections	Visits	Original Quantity	Insp Rec
LV Mains		3			500	
HV Mains		3			500	
Trenchless		3			0	
LV Joints		3			30	
LV Terminations		3			10	
HV Joints		3			2	
HV Terminations		3			1	
Pole erection		3			0	
Spans of conductor installation		3			0	
Final climbing inspection		3			0	

Total Completed Visits **0**

**Cancel**

rt\_inspection\_drawdown

On accessing the Draw down tool you will need to:

1. Check the ICP displayed is correct.
2. Enter the ICP scheme of work into the 'Temp Quantity' column.
3. Click 'Calculate'

1. →

ICP **STERLING POWER UTILIT** Category **Mains** **Calculate** ← 3.

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required.

Activity	Temp Quantity	Inspection Level	Inspections	Visits	Original Quantity	Inspections Required	Inspections Outstanding	Inspections Complete	Not Required
LV Mains		3			500		1	0	
HV Mains		3			500		1	0	
Trenchless		3			0		0	0	
LV Joints		3			30		1	0	
LV Terminations		3			10		1	0	
HV Joints		3			2		1	0	
HV Terminations		3			1		1	0	
Pole erection		3			0		0	0	
Spans of conductor installation		3			0		0	0	
Final climbing inspection		3			0		0	0	

Total Completed Visits **0**

**Cancel**

2. →

rt\_inspection\_drawdown

On clicking 'Calculate' the Inspections required will be displayed showing how much needs to be checked out of the full amount of the ICP work.

ICP **STERLING POWER UTILIT** Category **Mains** **Calculate**

Please confirm the ICP for the scheme and the category for the activities that are to be inspected  
Please enter the quantities of each activity as required, and pressing the calculate button will update the number of inspections required.

Activity	Temp Quantity	Inspection Level	Inspections	Visits	Original Quantity	Inspections Required	Inspections Outstanding	Inspections Complete	Not Required
LV Mains	500	3	100	1	500		1	0	
HV Mains	200	3	100	1	500		1	0	
Trenchless		3			0		0	0	
LV Joints	4	3	5	1	30		1	0	
LV Terminations	2	3	2	1	10		1	0	
HV Joints		3			2		1	0	
HV Terminations	2	3	2	1	1		1	0	
Pole erection		3			0		0	0	
Spans of conductor installation		3			0		0	0	
Final climbing inspection		3			0		0	0	

Total Completed Visits **0**

**Cancel**

rt\_inspection\_drawdown

When presented with the results, it is important to write them down before changing the category, as CROWN will not save the information, and you will lose it.

## CROWN Recording of Site Inspection Results (WPD & ICP works)

When the inspection forms are returned, the information must be entered into CROWN. This task will normally be carried out by a Team support; a separate user guide outlining this process in detail is available.

To view the guidance for the CROWN Inspection recording processes click on or navigate to <\\AVODCS01\NEWCON\CIC\I and MR\CROWN inspection recording.pdf.lnk>

### Important

Where an inspection is undertaken at SIL 1 or SIL2 DO NOT record a visit, only record a visit where a re-inspection is being undertaken at SIL1 or SIL2.

## Adding additional Inspections

Open the ICP Inspection activity

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
18	Services - Polarity and Lo	Smith, Paul	28/08/201	27/08/201	Passed	
19	Services - Service Joints	Smith, Paul	28/08/201	27/08/201	Passed	
20	Substations - Foundations	Smith, Paul	28/08/201	27/08/201	Passed	
21	Substations - Transformer	Smith, Paul	28/08/201	27/08/201	Passed	
22	Substations - HV Substati	Smith, Paul	28/08/201	27/08/201	Passed	
23	Mains - HV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
24	Mains - HV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
25	Mains - LV Joints	Smith, Paul	27/08/201	27/08/201	Passed	
26	Mains - LV Joints	Smith, Paul	27/08/201	27/08/201	Failed	Category 3
27	Mains - LV Terminations	Smith, Paul	27/08/201	27/08/201	Passed	

Where an additional Inspection needs to be added, click the add button.

Select the appropriate activity to be inspected

ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List

Activity  Inspection Result

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
18	Services - Polarity and Lo	Smith, Paul	28/08/201	27/08/201	Passed	
19	Services - Service Joints	Smith, Paul	28/08/201	27/08/201	Passed	
20	Substations - Foundations	Smith, Paul	28/08/201	27/08/201	Passed	
21	Substations - Transformer	Smith, Paul	28/08/201	27/08/201	Passed	
22	Substations - HV Substati	Smith, Paul	28/08/201	27/08/201	Passed	
23	Mains - HV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
24	Mains - HV Mains	Smith, Paul				
25	Mains - LV Joints	Smith, Paul				
26	Mains - LV Joints	Smith, Paul				
27	Mains - LV Terminations	Smith, Paul				

Add Save

Find %

ACTIVITY

- Mains - LV Mains
- Mains - HV Mains
- Mains - Trenchless
- Mains - LV Joints
- Mains - LV Terminations
- Mains - HV Joints
- Mains - HV Terminations
- Mains - Pole erection
- Mains - Spans of conductor installation

Find OK Cancel

CROWN has now created an additional inspection

ICP Inspections

Specify Inspection Details and whether the inspection passed, failed or was not required. Subsequent inspections can be added using the Add button. Please note that for the Send Inspection Report activity only inspections that were Passed or Failed will be shown. Use the dropdown lists at the top to filter Inspections List

Activity  Inspection Result

Inspection Number	Activity	Inspector	Target Date	Completion Date	Result	Defect Category
20	Substations - Foundations	Smith, Paul	28/08/201	27/08/201	Passed	
21	Substations - Transformer	Smith, Paul	28/08/201	27/08/201	Passed	
22	Substations - HV Substati	Smith, Paul	28/08/201	27/08/201	Passed	
23	Mains - HV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
24	Mains - HV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
25	Mains - LV Joints	Smith, Paul	27/08/201	27/08/201	Passed	
26	Mains - LV Joints	Smith, Paul	27/08/201	27/08/201	Failed	Category 3
27	Mains - LV Terminations	Smith, Paul	27/08/201	27/08/201	Passed	
28	Mains - LV Mains	Smith, Paul	27/08/201	27/08/201	Passed	
29	Mains - LV Joints		27/08/201			

Add Save Close

rt\_icp\_inspections

## Section 4 – FAQ's

FAQ	Answer	Relevant links / guides
Where are the blank report forms	<a href="#">NEWCON &gt; CIC &gt; I&amp;MR &gt; Forms for I&amp;MR</a>	<a href="#">click here</a>
How do I work out the estimated number of inspection visits required for my option 2 quote?	Using the estimation calculator located in the <a href="#">NEWCON drive</a> . Follow the on screen instructions, and refer to the operation manual.	<a href="#">click here</a>
How do I include the charge for the estimated number of inspection in option 2 of my dual offer?	Include the estimated inspection costs against the CIC category.	<a href="#">click here</a>
Do I include 'on costs' for the inspection costs?	No – on costs must be zeroed	List of items on-costs to be zeroed <a href="#">click here</a> page 3
I have used Diary instead of Trackable for an activity, how do i change this?	Select the activity to be changed – click Expand – change the selection to trackable – save and close.	<a href="#">click here</a>
When do I complete 'Design Approval Requested'?	Only when the ICP has sent you their design for approval. This activity <u>does not</u> represent you requesting their design.	
On completing Design approval I do not see the inspection calculator window appear?	You have not completed the 'Enter ICP information' activity prior to attempting to approval the design.  CROWN needs you to complete 'Enter ICP Information' first so that it can base the calculation on the ICP's inspection level.  Reactivate design approval – complete 'Enter ICP information' – carry out design approval again. You should now be presented with the inspection calculator.	
A list of all user guides and manuals associated with I&MR 2015	<ol style="list-style-type: none"> <li>1. <a href="#">ST:NC2M</a> <a href="#">click here</a></li> <li>2. <a href="#">Team support I&amp;MR user-guide</a> <a href="#">click here</a></li> <li>3. <a href="#">Technician / inspectors I&amp;MR user-guide</a> <a href="#">click here</a></li> </ol>	



# Section 5 - Documentation

## Contents

WPD Inspection and Monitoring Regime Notice of Inspection..... 62

Defect Notices ..... 62

Inspection Report Forms ..... 62

Defect Category Guidance..... 63

## WPD Inspection and Monitoring Regime Notice of Inspection

This is a formal notice of Inspection

Following the program of works submitted, WPD have made a site visit to carry out an Inspection in accordance with the Inspection Regime.





Please find attached to these document details of the inspections that have been undertaken. If you are at Inspection Level 1 or 2 for any Activity inspected the inspections will count to a movement to the next lower inspection level.

If you are at inspection Level 3 the successfully inspected assets will ensure that you remain at the lowest level of inspection.

### Defect Notices

The following defect notices are available in the NEWCON shared area










<N:\CIC\I and MR\Forms for I&MR\Inspection notices>

 WPD Defect Notice of an Energised Netw...	08/09/2014 15:13	Adobe Acrobat D...	116 KB
 WPD Defect Report	08/09/2014 15:22	Adobe Acrobat D...	115 KB
 WPD Inspection and Monitoring Regime ...	08/09/2014 15:26	Adobe Acrobat D...	111 KB
 WPD Rejection Notice	08/09/2014 15:29	Adobe Acrobat D...	41 KB

### Inspection Report Forms















The following Inspection and Monitoring forms are available in the NEWCON shared area

<N:\CIC\I and MR\Forms for I&MR>

 ASSOCIATED 11KV PRIMARY SWITCHGE...	10/08/2015 08:31	Adobe Acrobat D...	210 KB
 EHV MAINS OVERHEAD REPORT	10/08/2015 08:31	Adobe Acrobat D...	224 KB
 EHV MAINS UNDERGROUND REPORT	10/08/2015 08:30	Adobe Acrobat D...	232 KB
 EHV SUBSTATIONS - CIVIL REPORT	10/08/2015 08:30	Adobe Acrobat D...	213 KB
 EHV SUBSTATIONS - PLANT REPORT	10/08/2015 08:29	Adobe Acrobat D...	265 KB
 FINAL CONNECTIONS REPORT	10/08/2015 08:29	Adobe Acrobat D...	207 KB
 MAINS SITE REPORT FORM V3	19/05/2015 15:35	Adobe Acrobat D...	233 KB
 SERVICE SITE REPORT FORM V3	19/05/2015 15:36	Adobe Acrobat D...	239 KB
 SUBSTATION SITE REPORT FORM V3	19/05/2015 15:37	Adobe Acrobat D...	237 KB

## Defect Category Guidance

The following Defect Category guidance documents are available in the NEWCON shared area [N:\CIC\I and MR\Forms for I&MR\Defect category guidance](#)

 11kV Sub extesible circuit breaker Inspec...	08/09/2014 14:57	Adobe Acrobat D...	165 KB
 11kV Distrabution Sub extesible type in G...	08/09/2014 14:57	Adobe Acrobat D...	219 KB
 11kV Distrabution Sub unit type with non...	08/09/2014 14:58	Adobe Acrobat D...	224 KB
 11kV Distrabution Sub unit type with RM...	08/09/2014 14:58	Adobe Acrobat D...	230 KB
 33kV Sub extesible circuit breaker Inspec...	10/08/2015 08:21	Adobe Acrobat D...	286 KB
 66kV Sub circuit breaker inspection	10/08/2015 08:22	Adobe Acrobat D...	249 KB
 132kV Sub circuit breaker inspection	10/08/2015 08:23	Adobe Acrobat D...	249 KB
 CiC Inspection LV	08/09/2014 14:59	Adobe Acrobat D...	277 KB
 CiC Inspection OH 11-33KV	10/08/2015 08:23	Adobe Acrobat D...	333 KB
 CiC Inspection OH LV	08/09/2014 14:59	Adobe Acrobat D...	361 KB
 CiC Inspection OH MV	08/09/2014 14:59	Adobe Acrobat D...	331 KB
 Overhead Inspection Report	20/02/2015 09:18	Adobe Acrobat D...	257 KB
 Quality Index 11kV Jointing Inspection De...	08/09/2014 15:02	Adobe Acrobat D...	131 KB
 Quality Index Cable Laying Inspection De...	10/08/2015 08:24	Adobe Acrobat D...	211 KB
 Quality Index Cable Laying Inspection De...	08/09/2014 15:02	Adobe Acrobat D...	207 KB
 Substation Acceptance Process	10/08/2015 08:25	Adobe Acrobat D...	300 KB

## **APPENDIX B**

### **SUPERSEDED DOCUMENTS**

None.

## **APPENDIX C**

### **ASSOCIATED DOCUMENTATION**

The Electricity Act 1989 as amended by the Utilities Act 2000  
The Electricity (Connection Charges) Regulations 2002  
The Electricity Safety Quality and Continuity Regulations 2003  
Western Power Distribution (South West) plc's Distribution Licence  
Western Power Distribution (South Wales) plc's Distribution Licence  
Western Power Distribution (East Midlands) plc's Distribution Licence  
Western Power Distribution (West Midlands) plc's Distribution Licence  
Statement of Methodology and Charges for Connection to Western Power Distribution (South West) plc's Electricity Distribution System;  
Statement of Methodology and Charges for Connection to Western Power Distribution (South Wales) plc's Electricity Distribution System;  
Statement of Methodology and Charges for Connection to Western Power Distribution (East Midlands) plc's Electricity Distribution System;  
Statement of Methodology and Charges for Connection to Western Power Distribution (West Midlands) plc's Electricity Distribution System  
POL HS9 and associated STs - CDM Regulations  
POL: NC2 New Connections

## **APPENDIX D**

### **REVIEW DATE**

This document shall be reviewed in September 2018

## **APPENDIX E**

### **KEY WORDS**

Network Access and Adoption Agreement, Connection Offer, ICP, Inspection, Specification, Defect.