

## MK7C

## Set A Scrolling Display

Set	LCD Desc	Display	Unit	Displayed	Description
A	TIME	tlnE		HH:MM:SS	Current Time (DLS Applied)
A	DATE	dAtE		DD.MM.YY	Current Date (DLS Applied)
A	R1	r1	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Rate A
A	R2	r2	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Rate B
A	TO	to	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Unified
A	WPD	uPd		08457448900	Vendor Phone Number

## Set B displayed by holding down SELECT Button on MK7C

B	MDIW	ndlu	KW	0.00	Max D, CH1: Import wh Total, Current, Unified
B	MDIV	ndlu	KVA	0.00	Max D, CH5: Import VAh Total, Current, Unified
B	MDIT	ndlt		HH:MM:SS	Max DT, CH1: Import wh Total, Current, Unified
				DD.MM.YY	
B	MDIC	ndIC		1	Billing Reset Count
B	EW	Eu	KWh	0	Accum, CH2: Export wh Total, Cumulative Total, Unified
B	EVA	EuA	KVAh	0	Accum, CH6: Export VAh Total, Cumulative Total, Unified
B	GSM	GSn		99	Modem Signal Strength
B	VL1	uL1	V	000.000	Voltage
B	IL1	IL1	A	0.000	Main Current
B	POW	Pou	KW	0.0000	Active Power (Total)
B	PF	PF		1.000	Power Factor
B	FREQ	FrEq		00.000	Frequency
B	SSC	SSC		SSC_0000	Miscellaneous String

## MK10A WC/CT

## Set A Scrolling Display

Set	LCD Desc	Display	Unit	Displayed	Description
A	TIME	tlnE		HH:MM:SS	Current Time (DLS Applied)
A	DATE	dAtE		DD.MM.YY	Current Date (DLS Applied)
A	R1	r1	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Rate A
A	R2	r2	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Rate B
A	TO	to	KWh	00000000	Accum, CH1: Import wh Total, Cumulative Total, Unified
A	WPD	uPd		08457448900	Vendor Phone Number

## Set B displayed by holding down Display Select Button on MK10a

B	IVAR	IuAr	KVArh	0	Accum, CH3: Import varh Cumulative Total, Unified
B	IVA	IuA	KVAh	0	Accum, CH5: Import VAh Cumulative Total, Unified
B	MDIW	ndlu	KW	0.00	Max D, CH1: Import wh Total, Current, Unified
B	MDIVA	ndluA	KVA	0.00	Max D, CH5: Import VAh Total, Current, Unified
B	MDIT	ndlt		HH:MM:SS	Max DT, CH1: Import wh Total, Current, Unified
				DD.MM.YY	
B	MDIC	ndIC		0	Billing Reset Count
B	EW	Eu	KWh	0	Accum, CH2: Export wh Total, Cumulative Total, Unified
B	EVAR	EuAr	KVArh	0	Accum, CH4: Export varh Total, Cumulative Total, Unified
B	EVA	EuA	KVAh	0	Accum, CH6: Export VAh Total, Cumulative Total, Unified
B	GSM	GSn		99	Modem Signal Strength
B	VL1	uL1	V	000.000	Phase A Voltage
B	VL2	UI2	V	000.000	Phase B Voltage
B	VL3	uL3	V	000.000	Phase C Voltage
B	IL1	IL1	A	0.000	Phase A Current
B	IL2	IL2	A	0.000	Phase B Current
B	IL3	IL3	A	0.000	Phase C Current
B	POW	Pou	KW	0.0000	Active Power (Total)
B	CT	Ct		1	Primary Current Ratio
B	PF	PF		1.000	Power Factor
B	FREQ	FrEq		00.000	Frequency
B	SSC	SSC		SSC_0000	Miscellaneous String